
## **Termination instructions**

## for 012-021 RJ45 modular plug

Start with removing the outer jacket and preparing the conductors.
Use a piece of the cable jacket to help unwind and straighten the conductor.





4 Cut extra cable leaving about 34"

Line up your color code and cut the conductor at an angle. This will help while inserting the load bar.





Insert to housing and terminate using the proper tool.

Note: Before crimping the plug remove the center teeth/cast from the termination tool.

This will prevent damages to the housing case.

Tool used: 078-1017

Note: pin 1 – orange/white conductor needs to be inserted on the bottom left of the load bar. If reversed the conductors will not line up with the

termination points.







Crimp and fold down the cable holder (located on back of connector) to secure the ground wire and cable